

24 Hour Programmable Timer Switch

TM256

Please read the instructions fully before attempting installation.

IMPORTANT

This unit should be installed to current IEE wiring regulations.

- Timer must not be mounted on a flammable surface.
- Ensure that the timer does not come into contact with any combustible material such as towels or bedding.
- Ensure at least a 300mm airspace is allowed around the timer.
- The timer should not be mounted on an unearthed metal or metallised surface.
- If the timer is to be connected to an appliance that is required to be earthed. The supply earthing conductor and the appliance earthing conductor should be terminated together in the earth terminal provided within the timer.

Technical Specifications

Programming Capacity	96 On/Off programmes in total
Resistive Load	16A
Inductive Load	4A
Maximum Wattage	3000w (1000w CFL/LED)
Minimum Switching	15 Minutes
Override	On / Auto
Class II Control / Protection Class	IP20

Installation

1. Switch off electric at the mains.
2. Prepare cable ends for connection to the terminals.
3. Remove the 1 screw holding the timer switch terminal cover. **DO NOT INTERFERE WITH ANY OF THE FIXED CONNECTIONS.**
4. Connect all earth wires to earthing points.
5. Wire timer in accordance to wiring diagram on the unit.
6. Use lower screw hole to secure unit to wall plus the mounting hole on rear of unit.
7. Carefully replace terminal cover ensuring all wires are stowed neatly and not trapped.
8. Replace screw and tighten.

Wiring Connections

Ensure the earth to the switched appliance is maintained.

Timer to be wired in accordance with wiring diagram on unit.

Any electrical work should be carried out by a qualified electrician.

Setting The Clock

- Turn the dial in the direction of the arrow (clockwise) until the correct time of day is shown on the hands of the clock. The time now arrow should also correspond with the correct time of day.
- For the "ON" period push the switching riders out towards the edge of the face. The timer will operate for the duration set (each segment is approximately 15 minutes) i.e. if it is required to switch on between 16:00 and 18:00, all the segments between these times should be moved to the outer edge.

Setting The Programme

- By moving the switch located centre right of the clock face the following can be achieved

ON = Permanently ON

Auto = Switching programme as set on dial

- To switch permanently "OFF" the entire timer switch riders will need to be moved to the 'inwards' position.

UKCA Information

Complies with European Norm
EN 61058-12002 +A2:2008



Switches for Appliances: General Requirements and European Directives: LVD; EMC; RoHS; RED

Guarantee

This 24 Hour Programmable Timer Switch is guaranteed for a period of 12 months from date of purchase.

Please retain for future reference